File E62388 Project 07SC02612

July 27, 2007

REPORT

ON

COMPONENT - ELECTROMAGNETIC INTERFERENCE FILTERS

Tdk Corp. Inductive Devices Div. Yuri-Gun, Japan

Copyright © 2007 Underwriters Laboratories Inc.

Underwriters Laboratories Inc. authorizes the above-named company to reproduce this Report provided it is reproduced in its entirety.

Underwriters Laboratories Inc. authorizes the above-named company to reproduce that portion of this Report consisting of this Cover Page through Page 3.

File E62388 Vol. 13 Sec. 2 Page 1 Issued: 2007-07-27 and Report Revised: 2008-10-06

DESCRIPTION

PRODUCT COVERED:

USR Component - Electromagnetic Interference Appliance Filters,

Model RSHN-2003, RSHN-2006, RSHN-2010, RSHN-2016, RSHN-2020, RSHN-2030,

Model RSHN-2003L, RSHN-2006L, RSHN-2010L, RSHN-2016L, RSHN-2020L, RSHN-2030L,

Model RSHN-2040, RSHN-2050, RSHN-2060,

Model RSMN-2003, RSMN-2006, RSMN-2010, RSMN-2016, RSMN-2020, RSMN-2030,

Model RSMN-2003L, RSMN-2006L, RSMN-2010L, RSMN-2016L, RSMN-2020L, RSMN-2030L,

Model RSMN-2040, RSMN-2050, RSMN-2060.

*

File E62388 Vol. 13 Sec. 2 Page 1A Issued: 2007-07-27 and Report New: 2008-10-06

ELECTRICAL RATINGS:

	Volts	Current	Frequency.		Maximum
Catalog. No.	(V ac)	(A)	(Hz)	Phase	Ambient (°C)
RSHN-2003	250	3	50/60	1	55
RSHN-2003L					
RSMN-2003					
RSMN-2003L					
RSHN-2006	250	6	50/60	1	55
RSHN-2006L					
RSMN-2006					
RSMN-2006L RSHN-2010	250	10	E0/C0	1	55
RSHN-2010 RSHN-2010L	250	10	50/60	1	55
RSMN-2010L RSMN-2010					
RSMN-2010					
RSHN-2016	250	16	50/60	1	55
RSHN-2016L	230	10	30700	Δ.	33
RSMN-2016					
RSMN-2016L					
RSHN-2020	250	20	50/60	1	55
RSHN-2020L					
RSMN-2020					
RSMN-2020L					
RSHN-2030	250	30	50/60	1	55
RSHN-2030L					
RSMN-2030					
RSMN-2030L					
RSHN-2040	250	40	50/60	1	55
RSMN-2040					
RSHN-2050	250	50	50/60	1	55
RSMN-2050					
RSHN-2060	250	60	50/60	1	55
RSMN-2060					

File E62388 Vol. 13 Sec. 2 Page 2 Issued: 2007-07-27 and Report Revised: 2008-10-06

TECHNICAL CONSIDERATIONS (NOT FOR FIELD REPRESENTATIVE'S USE):

For use only in complete equipment where the acceptability of the combination is determined by Underwriters Laboratories Inc. The following are among the features which should be judged during the investigation of the equipment in which this filter is used:

Models have been judged on the basis of the spacing requirements in the Standard for Electromagnetic Interference Filters (UL 1283 Fifth Edition) which would cover the component itself if submitted for unrestricted Listing.

*USR - Indicates investigation to the Standard for Electromagnetic Interference Filters, UL 1283, Fifth Edition, latset revision dated July, 31, 2007.

File E62388 Vol. 13 Sec. 2 Page 3 Issued: 2007-07-27 and Report Revised: 2008-10-06

Conditions of Acceptability -

*1. The maximum leakage current measured on the model are tabulated below.

The suitability shall be determined in the end use application.

Model	At normal operation (mA)	At reverse operation (mA)
RSHN-2030	1.0	1.0
RSHN-2060	0.42	0.42

- 2. The end product shall not rely on the filter for grounding.
- 3. The filter should be provided with an overall enclosure suitable for the applicable end-product requirements.
- 4. The electrical ratings specified should not be exceeded.
- 5. These filters are not intended for use in radio, television, video, telephone, or telephone power supply type appliances.
- 6. The terminals have not been evaluated as field wiring terminals and shall be used for factory wiring only.
- 7. Suitability of mounting is to be determined in the end use product.
- 8. Suitability of grounding is to be determined in the end use product.
- 9. Polymeric covers have not been evaluated for mechanical strength of insulation.